



Wi-SUN SDK 2.0.0.0 GA

Simplicity SDK Suite 2024.6.0

June 5, 2024

Wireless Smart Ubiquitous Network (Wi-SUN) is the leading IPv6 sub-GHz mesh technology for smart city and smart utility applications. Wi-SUN brings Smart Ubiquitous Networks to service providers, utilities, municipalities/local government, and other enterprises, by enabling interoperable, multi-service, and secure wireless mesh networks. Wi-SUN can be used for large-scale outdoor IoT wireless communication networks in a wide range of applications covering both line-powered and battery-powered nodes.

Silicon Labs' Wi-SUN hardware is certified by the Wi-SUN Alliance, a global industry association devoted to seamless LPWAN connectivity. Wi-SUN builds upon open standard internet protocols (IP) and APIs, enabling developers to extend existing infrastructure platforms to add new capabilities. Built to scale with long-range capabilities, high-data throughput and IPv6 support, Wi-SUN simplifies wireless infrastructure for industrial applications and the evolution of smart cities.

These release notes cover SDK versions:

2.0.0.0 released June 5, 2024.



KEY FEATURES

Wi-SUN Stack

- Dropped the legacy socket API
- Stability improvements
- Removed support for Series 0/1

Wi-SUN Applications

- Underlying platform changes only

Compatibility and Use Notices

For information about security updates and notices, see the Security chapter of the Platform Release Notes installed with this SDK or on the TECH DOCS tab on <https://www.silabs.com/developers/wi-sun-protocol-stack>. Silicon Labs also strongly recommends that you subscribe to Security Advisories for up-to-date information. For instructions, or if you are new to the Silicon Labs Wi-SUN SDK, [Using This Release](#).

Compatible Compilers:

IAR Embedded Workbench for ARM (IAR-EWARM) version 9.40.1

- Using wine to build with the larBuild.exe command line utility or IAR Embedded Workbench GUI on macOS or Linux could result in incorrect files being used due to collisions in wine's hashing algorithm for generating short file names.
- Customers on macOS or Linux are advised not to build with IAR outside of Simplicity Studio. Customers who do should carefully verify that the correct files are being used.

GCC (The GNU Compiler Collection) version 12.2.1, provided with Simplicity Studio.

Contents

- 1 Wi-SUN Stack 3
 - 1.1 New Items..... 3
 - 1.2 Improvements..... 3
 - 1.3 Fixed Issues 3
 - 1.4 Known Issues in the Current Release 4
 - 1.5 Deprecated Items 4
 - 1.6 Removed Items 4
- 2 Wi-SUN Applications 5
 - 2.1 New Items..... 5
 - 2.2 Fixed Issues 5
 - 2.3 Known Issues in the Current Release 5
 - 2.4 Deprecated Items 5
 - 2.5 Removed Items 6
- 3 Using This Release 7
 - 3.1 Installation and Use..... 7
 - 3.2 Security Information..... 7
 - 3.3 Support..... 8

1 Wi-SUN Stack

Simplicity SDK is an embedded software development platform for building IoT products based on our Series 2 and Series 3 wireless and MCU devices. It integrates wireless protocol stacks, middleware, peripheral drivers, a bootloader, and application examples – a solid framework for building power-optimized and secure IoT devices.

The Simplicity SDK offers powerful features such as ultra-low power consumption, strong network reliability, support for a large number of nodes, and abstraction of complex requirements like multiprotocol and pre-certification. Additionally, Silicon Labs provides over-the-air (OTA) software and security updates to remotely update devices, minimize maintenance costs, and enhance the end-user product experience.

Simplicity SDK is a follow-on from our popular Gecko SDK, which will continue to be available providing long-term support for our Series 0 and Series 1 devices. For additional information on the Series 0 and Series 1 devices please reference: [Series 0 and Series 1 EFM32/EZR32/EFR32 device \(silabs.com\)](#).

1.1 New Items

Added in release 2.0.0.0

- Dropped the support of our previous socket API. Only the Posix-like socket API remains.
- Split the stack into smaller software modules, offering more granularity to the selection of the feature set selected and reducing the flash and RAM footprints. A device can now either act as an FFN when only the FFN-support component is installed, an LFN when only the LFN-support component is installed, or can decide which profile will be used thanks to an API call during the initialization phase if both are installed. As a direct consequence, new libraries with new filenames are released. Added an example of select() implementation. It only works with socket file descriptors but is distributed in source and could be enriched to support new file descriptor types.
- Added support for sendmsg(), recvmsg() and getsockname().
- Extended the list of supported socket options.

1.2 Improvements

Changed In release 2.0.0.0

- Added a random delay before starting an LFN join sequence. It was causing a significant number of over-the-air collisions when starting multiple LFN at the exact same time.

1.3 Fixed Issues

Fixed in release 2.0.0.0

ID #	Description
1290487	Fixed an issue causing the radio to be stuck in RX. The cause has been identified as a race in the lower layers of the radio driver.
1287317	Fixed an invalid memory access in the timer and event lists.
1285497	Fixed multiple invalid counter and timer updates during state transitions and RPL parent updates. They were causing abusive router disconnections.
1275243	Fixed an invalid use of a link-local as a source address in the DAO. On rare occasions, routers were using a link-local source address in the outer IPv6 header.
1272406	Fixed the condition upon which the MAC reset the CCA failures counter. The CCA failures counter is increased after each CCA busy event. Once the counter reaches a value of 8, it increases the retry counter by one. The CCA failures counter was only reset after a successful transmission. It is now reset after every transmission.
1258384	Fixed an invalid PAN ID filter configuration that was preventing routers from connecting to a new border router after a PAN timeout.

1.4 Known Issues in the Current Release

Issues in bold were added since the previous release.

ID #	Description	Workaround
1119464	Packets sent when FSK FEC is enabled can infringe ARIB regulation.	Until this problem has been addressed correctly, the stack will refuse to start if both ARIB enforcement and FEC are enabled.
1067978	Packets sent using a PHY with a bandwidth larger than the base PHY's bandwidth can infringe ARIB regulation.	Limit the communications when using mode switch with ARIB enforcement enabled.
1176014	FG25 asserts with a RAIL_ASSERT_FAILED_RTCC_SYNC_STALE_DATA error code when entering EM2.	Do not allow the power manager to go to EM2 by adding a requirement on EM1 in the application.

1.5 Deprecated Items

None

1.6 Removed Items

None

2 Wi-SUN Applications

2.1 New Items

Added in release 2.0.0.0

- Wi-SUN SoC CLI
 - Added new ping settings, including the packet length, the packet sequence number, and the interval between two ping requests.
- OTA DFU remote control over CoAP for all settings of sl_wisun_ota_dfu_config.h (file name, URI path, ...)

2.2 Fixed Issues

Fixed in release 2.0.0.0

ID #	Description
1289218	Fixed Wi-SUN - SoC (CoAP) Meter packet fragmentation issues.
1283362	Fixed iPerf FINACK packet parser issue.
1296544	Fixed inet_pton return value handling.
1296797	Fixed broken json in CoAP packet printer.
1294628	Fixed remote CoAP CLI buffer handling for Wi-SUN - SoC Network Measurement. Cleaning previous buffer content.
1276803	Wi-SUN - SoC Network Measurement : "iperf get json" returns with "Invalid resolved buffer" until the first test.

2.3 Known Issues in the Current Release

Issues in bold were added since the previous release.

ID #	Description	Workaround
1067236	The border router RCP SPI interface is unstable when used with a throughput higher than 1 Mbytes/s	The use of border router RCP SPI interface is not recommended for the time being.
	Simplicity Studio – Network Analyzer: Wi-SUN Encrypted Packets are not supported Undecoded frames (only after Ack) according to PTI issues on Series 2	
1304230	In certain cases, proper packing of data structures is only ensured when using IAR compiler. However, this discrepancy can lead to issues when combining binaries built with both GCC and IAR in the network. The issue relates to all applications except: <ul style="list-style-type: none"> • Wi-SUN - CLI example • Wi-SUN - LFN CLI example • Wi-SUN - RCP 	Use exclusively one toolchain (either GCC or IAR) for the applications affected.

2.4 Deprecated Items

Four applications will be phased out, and instead, four new components will be recommended for use. This transition will bring in simplicity and also enhance overall flexibility.

- Wi-SUN - SoC UDP Client
- Wi-SUN - SoC UDP Server
- Wi-SUN - SoC TCP Client

- Wi-SUN - SoC TCP Server

2.5 Removed Items

None.

3 Using This Release

This release contains the following:

Wi-SUN stack library

Wi-SUN sample applications

Wi-SUN border router pre-compiled demos

Documentation

If you are a first time user, see <https://docs.silabs.com/wisun/latest/wisun-getting-started-overview/>

3.1 Installation and Use

The Wi-SUN SDK is provided as part of the Simplicity SDK, the suite of Silicon Labs SDKs. To quickly get started with the Simplicity SDK, install [Simplicity Studio 5](#), which will set up your development environment and walk you through Simplicity SDK installation. Simplicity Studio 5 includes everything needed for IoT product development with Silicon Labs devices, including a resource and project launcher, software configuration tools, full IDE with GNU toolchain, and analysis tools. Installation instructions are provided in the online [Simplicity Studio 5 User's Guide](#).

Alternatively, Simplicity SDK may be installed manually by downloading or cloning the latest from GitHub.

See https://github.com/SiliconLabs/simplicity_sdk for more information.

Simplicity Studio installs the Simplicity SDK by default in:

- (Windows): C:\Users\<<NAME>\SimplicityStudio\SDKs\simplicity_sdk
- (MacOS): /Users/<NAME>/SimplicityStudio/SDKs/simplicity_sdk

Documentation specific to the SDK version is installed with the SDK.

3.2 Security Information

Secure Vault Integration

This version of the stack does not integrate Secure Vault Key Management.

Security Advisories

To subscribe to Security Advisories, log in to the Silicon Labs customer portal, then select **Account Home**. Click **HOME** to go to the portal home page and then click the **Manage Notifications** tile. Make sure that 'Software/Security Advisory Notices & Product Change Notices (PCNs)' is checked, and that you are subscribed at minimum for your platform and protocol. Click **Save** to save any changes.

SILICON LABS Search Within the Support Portal for Cases, etc... SEARCH CATHERIN...

HOME CASES SOFTWARE RELEASES

Update Preference

WHAT EMAILS WOULD YOU LIKE TO RECEIVE?

Newsletters

- Community Monthly Newsletter
- Sales Newsletter
- Micrium Newsletter

Product Specific Notifications

- Product Information and Newsletter
- Software/Security Advisory Notices & Product Change Notices (PCNs)
- Technical Document Updates (Release Notes, Data Sheets, etc.)

SELECT THE PRODUCTS TO RECEIVE UPDATES FOR

Select/Unselect All

<input type="checkbox"/> Audio and Radio	<input type="checkbox"/> Power over Ethernet
<input type="checkbox"/> Interface	<input type="checkbox"/> Sensors
<input type="checkbox"/> Isolation	<input type="checkbox"/> TV and Video
<input type="checkbox"/> Modems and DAAs	<input type="checkbox"/> Voice
<input type="checkbox"/> Microcontrollers	<input type="checkbox"/> Wireless
<input type="checkbox"/> 8-bit MCUs	<input type="checkbox"/> Bluetooth Classic
<input checked="" type="checkbox"/> 32-bit MCUs	<input type="checkbox"/> Bluetooth Low Energy
<input type="checkbox"/> Timing	<input checked="" type="checkbox"/> Proprietary
<input type="checkbox"/> Clocks	<input type="checkbox"/> Wi-Fi
<input type="checkbox"/> Buffers	<input type="checkbox"/> ZigBee and Thread
<input type="checkbox"/> Oscillators	<input type="checkbox"/> Z-Wave
<input type="checkbox"/> CDR and PHY	

3.3 Support

Development Kit customers are eligible for training and technical support. Contact Silicon Laboratories support at <http://www.silabs.com/support>.

Simplicity Studio

One-click access to MCU and wireless tools, documentation, software, source code libraries & more. Available for Windows, Mac and Linux!



IoT Portfolio
www.silabs.com/IoT



SW/HW
www.silabs.com/simplicity



Quality
www.silabs.com/quality



Support & Community
www.silabs.com/community

Disclaimer

Silicon Labs intends to provide customers with the latest, accurate, and in-depth documentation of all peripherals and modules available for system and software implementers using or intending to use the Silicon Labs products. Characterization data, available modules and peripherals, memory sizes and memory addresses refer to each specific device, and "Typical" parameters provided can and do vary in different applications. Application examples described herein are for illustrative purposes only. Silicon Labs reserves the right to make changes without further notice to the product information, specifications, and descriptions herein, and does not give warranties as to the accuracy or completeness of the included information. Without prior notification, Silicon Labs may update product firmware during the manufacturing process for security or reliability reasons. Such changes will not alter the specifications or the performance of the product. Silicon Labs shall have no liability for the consequences of use of the information supplied in this document. This document does not imply or expressly grant any license to design or fabricate any integrated circuits. The products are not designed or authorized to be used within any FDA Class III devices, applications for which FDA premarket approval is required or Life Support Systems without the specific written consent of Silicon Labs. A "Life Support System" is any product or system intended to support or sustain life and/or health, which, if it fails, can be reasonably expected to result in significant personal injury or death. Silicon Labs products are not designed or authorized for military applications. Silicon Labs products shall under no circumstances be used in weapons of mass destruction including (but not limited to) nuclear, biological or chemical weapons, or missiles capable of delivering such weapons. Silicon Labs disclaims all express and implied warranties and shall not be responsible or liable for any injuries or damages related to use of a Silicon Labs product in such unauthorized applications.

Note: This content may contain offensive terminology that is now obsolete. Silicon Labs is replacing these terms with inclusive language wherever possible. For more information, visit www.silabs.com/about-us/inclusive-lexicon-project

Trademark Information

Silicon Laboratories Inc.[®], Silicon Laboratories[®], Silicon Labs[®], SiLabs[®] and the Silicon Labs logo[®], Bluegiga[®], Bluegiga Logo[®], EFM[®], EFM32[®], EFR, Ember[®], Energy Micro, Energy Micro logo and combinations thereof, "the world's most energy friendly microcontrollers", Redpine Signals[®], WiSeConnect, n-Link, EZLink[®], EZRadio[®], EZRadioPRO[®], Gecko[®], Gecko OS, Gecko OS Studio, Precision32[®], Simplicity Studio[®], Telegesis, the Telegesis Logo[®], USBXpress[®], Zentri, the Zentri logo and Zentri DMS, Z-Wave[®], and others are trademarks or registered trademarks of Silicon Labs. ARM, CORTEX, Cortex-M3 and THUMB are trademarks or registered trademarks of ARM Holdings. Keil is a registered trademark of ARM Limited. Wi-Fi is a registered trademark of the Wi-Fi Alliance. All other products or brand names mentioned herein are trademarks of their respective holders.



Silicon Laboratories Inc.
400 West Cesar Chavez
Austin, TX 78701
USA

www.silabs.com